

**Instruction Manual**

**TECHNICAL SPECIFICATION**

Model Number	F26000RC	F26100RC	F26200RC	F26200RC-d	F26300RC	F26300RC-d	F26400RC	F26400RC-d
Wattage	5W	7.5W	12.5W	13W	20.5W	21.5W	12.5W	13W
Voltage	220-240~	220-240~	220-240~	220-240~	220-240~	220-240~	220-240~	220-240~
Frequency	50/60Hz	50/60Hz	50/60Hz	50/60Hz	50/60Hz	50/60Hz	50/60Hz	50/60Hz
Dimmable	No	No	No	100%-10%	No	100%-10%	No	100%-10%
IP Rating	IP20 IP21 IP22 IP44		IP20 IP21 IP22 IP44		IP20 IP21 IP22 IP44		IP20 IP21 IP22 IP44	
Model Number	F27100RC	F27100RCv1	F27100RCv1-d	F28500RC	F51400RC			
Wattage	35.5W	20.5W	21.5W	27W	12.5W			
Voltage	220-240~	220-240~	220-240~	220-240~	220-240~			
Frequency	50/60Hz	50/60Hz	50/60Hz	50/60Hz	50/60Hz			
Dimmable	No	No	100%-10%	No	No			
IP Rating	IP20 IP21 IP22 IP44		IP20 IP21 IP22 IP44		IP20 IP21 IP22 IP44			

**CAUTIONS**

- Read the entire manual carefully before installation and operation.
- It is recommended that the installation or replacement be performed by a licensed and qualified electrician.
- DO NOT disassemble the luminaire. Doing so may result in lamp damage or malfunction.
- Switch off the power source before installation, replacement and cleaning.
- Wearing gloves during installation is recommended to ensure the luminaire is kept in the best condition.
- Before replacement of the luminaire, turn it off and allow it to cool down. Heat-

- resistant gloves are mandatory when handling the luminaire.
- The F26200RC-d/F26300RC-d/F26400RC-d/F27100RCv1-d is capable of linear dimming from 100% to 10% when working with most conventional dimmers for incandescent lamps or halogens. Please visit [www.megaman.cc](http://www.megaman.cc) for the list of compatible dimmers.
- The minimum safety distance from the illuminated object is 0.1m.
- The manufacturer accepts no liability for any damage resulting from the misuse of the luminaire or from when it is used with inappropriate equipment.
- Consult your dealer if you have any enquiries.

**ATTENTION**

- Instant start is allowed.
- Designed for indoor application.

- The operating temperature of the luminaire is -30°C to +40°C.

**Installation**

**Cut-Out Ø:**

Model No.	Cut-Out (mm)
F26000RC	85
F26100RC	105
F26200RC	125
F26200RC-d	125
F26300RC	150
F26300RC-d	150
F26400RC	85
F26400RC-d	85
F27100RC	200
F27100RCv1	200
F27100RCv1-d	200
F28500RC	200

**Safety Distance:**

Model No.	W (mm)	H (mm)
F26000RC	80	100
F26100RC	80	100
F26200RC	100	140
F26200RC-d	100	140
F26300RC	100	140
F26300RC-d	100	140
F26400RC	80	100
F26400RC-d	80	100
F27100RC	100	140
F27100RCv1	100	140
F27100RCv1-d	100	140
F28500RC	100	140

**Cut-Out Ø:**

Model No.	Cut-Out (mm)
F51400RC	L130 x W130

**Safety Distance:**

Model No.	W (mm)	H (mm)
F51400RC	100	140

**Power Cord Preparation (for screw-in type):**

Input Voltage 220-240V~

**Power Cord Preparation (for snap-in type):**

Input Voltage 220-240V~

**Correct Disposal of This Product**

This marking indicates that this product should not be disposed with other household wastes throughout the EU. To prevent possible harm to the environment or human health from uncontrolled waste disposal, recycle it responsibly to promote the sustainable reuse of material resources. To return your used device, please use the return and collection systems or contact the retailer where the product was purchased. They can take this product for environmental safe recycling.

**Neonlite Electronic & Lighting (HK) Ltd.**  
 31/F, AIA Kowloon Tower, Landmark East, 100 How Ming Street,  
 Kwun Tong, Kowloon, Hong Kong.

