



An exceptional LED lay-in fitting for use in high footfall applications where access is limited and maintenance difficult. Non dimming driver included.



## 36W Berto 36W Square UGR22 LED Panel 4000K / 80 Non-Dim Driver

<b>Product Code</b>	<b>130204</b>
<b>International Model Number</b>	<b>FPL70300V1-EX</b>
<b>Description</b>	<b>36W Berto 36W Square UGR22 LED Panel 4000K / 80 Non-Dim Driver</b>
<b>Watts</b>	<b>36W</b>
<b>Colour Temperature</b>	<b>4000K / 80</b>
<b>Lumens</b>	<b>3400lm</b>
<b>Dimmable</b>	<b>N</b>
<b>Lamp life L70</b>	<b>50,000hrs</b>
<b>Lamp life L90</b>	<b>25,000hrs</b>
<b>Beam Angle</b>	<b>110</b>
<b>Weight</b>	<b>195g</b>
<b>Dimensions</b>	<b>595x595x13</b>
<b>IP Rating</b>	<b>IP20</b>
<b>Shape</b>	<b>Square</b>
<b>Operating Temperature</b>	<b>-30° to +40°</b>

Last modified: 2019-10-24 15:48:24.

View online at <https://www.megamanuk.com/products/fixtures/led-panel/berto/130204/>