

The Megaman LED AR111 is the perfect low energy replacement for halogen AR111s. Less heat is emitted thanks to Megaman's patented Thermal Conductive Highway which reduces energy loss through heat. The 12W AR111, with reduced height and slimmer profile, replaces the 75W halogen AR111.

Driver: Megaman recommends Megaman Driver 140627. Tested on a standard switch. Please consult dimmer manufacturer for compatibility.



12W G53 AR111 24° Dimming 12V 4000K

Product Code	141340
International Model Number	ER2712d-75H24D
Description	LED 12W G53 AR111 Dimming 12V 4000K
Order in	1
Watts	12W
Cap	G53
Operating Hours (L70)	50000
Operating Hours (L90)	35000
Colour Temp	4000K
CRI	85
Lumens	850lm
Candelas	5000cd
Dimming	Yes
Beam	24
Dimensions	58 x 111
Weight	230g
Energy Class	A
Operating Temperature	-30 C to +40 C

Last modified: 2016-10-21 15:16:12.

Extend your warranty
to 5 years!

MEGAMAN®



See how much you could

save by switching to

MEGAMAN® LEDs.



View online at <https://www.megamanuk.com/products/led-lamps/reflector/ar111/141340/>

Megaman (UK) Limited, Megaman House, 2 Quadrant Park, Mundells, Welwyn Garden City, Herts, AL7 1FS
Telephone: +44 (0) 1707 386000 , **Email:** sales@megamanuk.com **Website:** www.megamanuk.com

