

The Megaman LED AR111 is the perfect low energy replacement for halogen AR111s. Less heat is emitted thanks to Megaman's patented Thermal Conductive Highway which reduces energy loss through heat.



## LED 10W G53 Dimming 20V AR111, 8°, 2800K

<b>Product Code</b>	141341
<b>International Model Number</b>	ER0210-50H08D
<b>Description</b>	LED 10W G53 Dimming 20V AR111, 8°, 2800K
<b>Order in</b>	1
<b>Watts</b>	10W
<b>Cap</b>	G53
<b>Operating Hours (L70)</b>	50000
<b>Operating Hours (L85)</b>	40000
<b>Colour Temp</b>	2800k
<b>CRI</b>	82
<b>Lumens</b>	550 lm
<b>Intensity</b>	16000 cd
<b>Dimming</b>	Yes
<b>Beam</b>	8°
<b>Dimensions</b>	58 x 111 length x dia
<b>Weight</b>	218g
<b>Energy Class</b>	A
<b>Operating Temperature</b>	-30 C to +40 C
<b>Additional Info</b>	Use the Megaman 10W AR111 20V dimming driver, 141382, sold separately. Converts 220-240V to DC20V 500mA. Works with DC1-10V dimmer. Please contact our sales office for further dimming information.

Last modified: 2017-07-17 16:29:02.

[Extend your warranty](#)

View online at <https://www.megamanuk.com/products/led-lamps/reflector/ar111/141341/>