

The Megaman LED AR111 is the perfect low energy replacement for halogen AR111s. Less heat is emitted thanks to Megaman's patented Thermal Conductive Highway which reduces energy loss through heat. The 12W AR111, with reduced height and slimmer profile, replaces the 75W halogen AR111.

Driver: Megaman recommends Megaman Driver 140627. Tested on a standard switch. Please consult dimmer manufacturer for compatibility.



12W G53 AR111 45° Dimming 12V 2800K

Product Code	141409
International Model Number	ER2912d-75H45D
Description	LED 12W G53 AR111 Dimming 12V 2800K
Order in	1
Watts	12W
Cap	G53
Operating Hours (L70)	50000
Operating Hours (L90)	35000
Colour Temp	2800K
CRI	82
Lumens	850lm
Candelas	2000cd
Dimming	Yes
Beam	45
Dimensions	58 x 111
Weight	230g
Energy Class	A
Operating Temperature	-30 C to +40 C

Last modified: 2017-08-23 12:03:37.

Extend your warranty
to 5 years!

MEGAMAN®



See how much you could
save by switching to
MEGAMAN® LEDs.



View online at <https://www.megamanuk.com/products/led-lamps/reflector/ar111/141409/>

Megaman (UK) Limited, Megaman House, 2 Quadrant Park, Mundells, Welwyn Garden City, Herts, AL7 1FS
Telephone: +44 (0) 1707 386000 , **Email:** sales@megamanuk.com **Website:** www.megamanuk.com

