

The Megaman LED AR111 is the perfect low energy replacement for halogen AR111s. Less heat is emitted thanks to Megaman's patented Thermal Conductive Highway which reduces energy loss through heat.



## 18W G53 Dimming 36V AR111, 45°, 2800K

<b>Product Code</b>	<b>141740</b>
<b>International Model Number</b>	<b>ER2218d-100H45D</b>
<b>Description</b>	<b>LED 18W G53 Dimming 36V 500mA AR111, 45°, 2800K</b>
<b>Order in</b>	<b>1</b>
<b>Watts</b>	<b>18W</b>
<b>Cap</b>	<b>G53</b>
<b>Operating Hours (L70)</b>	<b>50000</b>
<b>Operating Hours (L90)</b>	<b>25000</b>
<b>Colour Temp</b>	<b>2800k</b>
<b>CRI</b>	<b>80</b>
<b>Lumens</b>	<b>1500 lm</b>
<b>Intensity</b>	<b>2600 cd</b>
<b>Dimming</b>	<b>Yes</b>
<b>Beam</b>	<b>45°</b>
<b>Dimensions</b>	<b>62 x 111 length x dia</b>
<b>Weight</b>	<b>221g</b>
<b>Energy Class</b>	<b>A</b>
<b>Driver</b>	<b>Megaman recommend the Sunpower PCC50018TD Triac Dimming 18W 500mA Constant Current LED driver</b>

Last modified: 2016-08-24 11:07:54.

**Extend your warranty**  
to 5 years!

**MEGAMAN®**



View online at <https://www.megamanuk.com/products/led-lamps/reflector/ar111/141740/>

**Megaman (UK) Limited**, Megaman House, 2 Quadrant Park, Mundells, Welwyn Garden City, Herts, AL7 1FS  
**Telephone:** +44 (0) 1707 386000 , **Email:** [sales@megamanuk.com](mailto:sales@megamanuk.com) **Website:** [www.megamanuk.com](http://www.megamanuk.com)

